

LED luminaire Emergency conversion kit - Max.50W



Product code:

Reference: BATERYPCTMBW

Technical specifications:

REFERENCE: BATERYPCTMBW
Rated Power : 3W-50W
Nominal Voltage: DC18V-175V
Construction Material: Thermoplastic
Certifications: CE - ROHS
IP : IP20
Dimensions (mm): 140x55x33mm
Frequency (Hz): 50/60Hz
Temperature Range (°C): -15° + 50°
Other Information: Battery 3.7V / 2.5Ah
Material of the Battery: LiFePO4 - Lithium-Ferrophosphate -LPF
Download Time: 50W: 50 minutes - 40w: 60 minutes - 30w: 75 minutes - 20w: 90 minutes
Energy Rating (2021-UE-2019/2015): A+
Warranty Years: 2

Product short description:

CONVERTS ALL TYPES OF LED LUMINAIRE - WITH DRIVER - IN EMERGENCY. With the 2500mAh emergency battery you will be able to convert any LED luminaire into an emergency. Its operation is by regulating the luminaire to 30% where you install it automatically. **Maximum of 50W. (Not suitable for Driverless products).**

Product description:

The battery has 2500 mAh (2.5Ah) of a range that depends on the consumption according to the watts of the luminaire where it is installed. The luminaire will regulate the luminous flux to 30% of its total power, resulting in a minimum duration of:

- 50W: Duration 50 minutes
- 40w: Duration 60 minutes
- 30w: Duration: 75 minutes
- 20w: Duration 90 minutes

The battery is installed by powering the luminaire's LED driver and connecting to the electrical network.

Additional images:



Technical Datasheet
