

60W LED Streetlight ASKER BRIDGELUX Chip 140lm/W



Product code:

Reference: SL60W

Technical specifications:

REFERENCE: 90357-60W
Rated Power : 60w
Nominal Voltage: 85-265V
Colour: 4000K-6000K
CRI - Chromatic Rendiment Index: 70
Construction Material: Alumininum+Glass
Luminosity-Lm: 8400Lm
Number & Type of LEDs: SMD3030 Bridgelux 1835DS-C30
Beam Angle (°): 140° x 52°
Luminous diodo LED (Lm/W): 180 Lm/W
Luminous Efficiency (Lm/W): 140 Lm/W
Certifications: CE-RoSH
IP : IP65-Outdoor
Diode Life Expectancy (H): 50.000
Dimensions (mm): 513x180x85mm - Tube hole 630mm
Power Factor (PF): 0.98
Frequency (Hz): 50/60Hz
Temperature Range (°C): -20°C ~ +55°C
On/Off Cycles: 100.000
Starting Time (s): 0,2s
Impact Protection (IK) : IK08
Driver included: Driver GXTronic - 5 Years
Energy Rating (2021-UE-2019/2015): A++
Energy Rating (2023 - UE-2019/2015): F
Warranty Years: 3

Product short description:

The **60W ASKER LED** Street Light is made of high-luminosity **Bridgelux SMD 3030** diodes, which are capable of generating great lighting in any outdoor public lighting space. The time has come to replace the old street lights with the new ones, and with LED technology it is possible to reduce energy consumption by up to 80%.

Product description:

60W ASKER BRIDGELUX LED Streetlight Chip 140lm/W

To achieve a better public lighting the ideal is the new **ASKER BRIDGELUX Chip LED** Street Light that stands out from the rest thanks to its **60W SMD3030** power achieving a quality luminaire. It is made of high quality aluminium and is therefore guaranteed to be highly resistant to the elements.

Thanks to its extra-flat design it prevents leaves or dirt from being deposited on it, while at the same time minimising its visual impact.

The **ASKER LED** street lamp is immediately switched on, eliminating the annoying waiting times that leave entire areas in darkness when the power supply fails, creating insecurity among passers-by.

Furthermore, thanks to its IP65 protection, it is protected against any climatic change, if its lighting function is affected.

The **ASKER LED** street lighting luminaire will enable you to maintain good lighting with low consumption. The operating cost is lower as there are no starters or electronics to replace.

Built for a long life of more than 50,000 hours, the **60W ASKER LED** street light has a **3** year guarantee for its high quality and durable power supply.

It has a 60mm diameter round swivel connector, fixing 2 pressure screws to the column.

Uses for ASKER BRIDGELUX 60W LED Streetlight 140lm/W Chip

- Public lighting
- Gardens and paths
- Parks and squares
- Sports centre
- Car parks

In FactorLED we assure that our products have a **QUALITY** guarantee and offer all the necessary elements for **DISTRIBUTION, IMPORT or WHOLESALE**, including the technical data sheet of each LED product.

Technical Datasheet

Additional images:



bridge_{lux}

bridge_{lux} lighting experts

SMD0608 BridgeLux 183505-C10

