

LED Tracklight 10W FENIX - Black Chrome - 3-PHASE Rails - CRI+93



Product code:

Reference: TRBC10W-CHROME

Technical specifications:

REFERENCE: TRBC10W-CHROME

Rated Power : 10W

Nominal Voltage: 175-265V

Colour: 3000K - 4000K

CRI - Chromatic Rendiment Index: 93

Construction Material: Aluminium +P MMA

Luminosity-Lm: 4800

Number & Type of LEDs: COB BRIDGELUX CHIP 2630 DS-C30

Beam Angle (°): 24°

Luminous diodo LED (Lm/W): 130Lm/W

Luminous Efficiency (Lm/W): 100 Lm/W

Certifications: CE - ROHS

IP : IP20

Diode Life Expectancy (H): 35.000

Frequency (Hz): 50/60Hz

Temperature Range (°C): -20° ~ +40°

On/Off Cycles: 100.000

Starting Time (s): 0,2s

Other Information: Painting: AkzoNobel Interpon 600 C33883

Energy Rating (2021-UE-2019/2015): A+

Warranty Years: 3

Product short description:

Our **10W -FENIX- 3-PHASE -black chrome- LED tracklight** incorporates a **BRIDGELUX COB chip**, with a very high chromatic resolution index of over +93, which makes the quality of the light unbeatable, and the realism of the colours almost perfect for highlighting specific elements. **24°** angle.

Product description:

LED Tracklight 10W FENIX - Black Chrome - 3-PHASE Rails - CRI+93

The **LED Tracklight -FENIX- BRIDGELUX Chip** of 10w is characterized because it has a design that will combine with any style and excellent performance.

The **FENIX LED Tracklight** has **BRIDGELUX Chip** is ideal for illuminating any place you want to highlight, it is also perfect for situations in spaces that are looking for class and distinction in its lighting network also you have it in different temperatures **3000k and 4000k**.

Its black chrome design is ideal for creating minimalist environments while highlighting the spaces you need to highlight. Its installation is simple to be placed in single-phase rail, now the decoration is in your hands and in the easiest way.

This product has been manufactured for special indoor use, hence its **IP20** protection.

Our **FENIX LED Tracklight** emits **1000 lumens** (COB BRIDGELUX CHIP 2630 DS-C30) and saves up to 90% on our bill. The spotlight is able to withstand voltage from **175V to 265V**.

Uses of the LED Tracklight 10W FENIX - Black Chrome - 3-PHASE Rails - CRI+93:

- Shop windows
- Offices
- Showcases
- Stores
- Art galleries
- Museums

In FactorLED we ensure that our products have **QUALITY** guarantee and offer all the necessary elements for **DISTRIBUTION, IMPORT or WHOLESALE**, including the technical data sheet of each LED product.

Technical Datasheet

Additional images:



bridgelux[®]
Bridging Light and Life™

