

DMX512 PRO Lighting Control Table - 512 channels



Product code:

Reference: 7908-PRO

Technical specifications:

REFERENCE: 7908-PRO
Rated Power : 4W
Nominal Voltage: AC 90-230V
Construction Material: Aluminium+PC
Certifications: CE - ROHS
IP : IP20
Dimensions (mm): 483 x 130 x 82 mm
Frequency (Hz): 50/60Hz
Temperature Range (°C): -20°C ~ +55°C
Other Information: LED Digital Display (2 x 16 caracteres)
Number of Channels: DMX512 : 512 Channels -Number of sequences: 9
Control modes: DMX
Warranty Years: 2

Product short description:

Discover our **DMX512-PRO Control Table**, designed to provide a hassle-free experience. **With 512 fully customizable DMX channels**, assignable to 32 control channels and **32 programmable scenes**, you can effortlessly create stunning effects. The LED digital display makes setup easy, while sound activation, TAP Sync, or automatic options add versatility to your arsenal. Additionally, it's compatible with voltages AC110-240V 50-60Hz. Simplify control at your events and elevate them to a new level with this reliable controller. Explore a new standard in lighting and entertainment.

Product description:

DMX512 PRO Lighting Control Table - 512 channels

Get ready to elevate your events to a new level with the impressive DMX512-PRO Console. Designed to offer a straightforward and uncomplicated control experience, this DMX table controller provides everything you need to create stunning lighting effects easily and accessibly.

With 512 fully customizable DMX channels, assignable to 32 control channels, you'll have precise control over your lights and effects, allowing you to create captivating atmospheres for every occasion. Whether you're organizing a party, a concert, or any other event, our control table offers the flexibility to adjust and customize every detail of your lighting.

The controller features 32 programmable scenes, allowing you to save specific lighting configurations and quickly access them. Additionally, you can memorize 32 programmable chases with 100 scenes each, giving you the ability to create complex and synchronized sequences that perfectly fit the atmosphere of your event.

To add even more versatility, our DMX512-PRO control table allows you to program chases to automate the creation of complex effects. The TAP Sync function allows you to synchronize the speed of lighting changes with the tempo of the music, providing a stunning and immersive visual experience.

Setup and control are intuitive thanks to the LED Digital Display, allowing you to navigate options clearly and simply. Furthermore, sound activation, TAP Sync, or automatic options enable you to seamlessly synchronize your lights with the music and other elements of the event.

The DMX table adapts to your voltage needs, with a range of AC110-240V 50-60Hz, providing the flexibility to take your lights anywhere.

In summary, the DMX512-PRO table is perfect for those seeking a simple and accessible control experience without sacrificing quality and versatility. Simplify your lighting control and let your events shine with this reliable and powerful controller.

Key Features:

- 512 freely invertible DMX channels assignable to 32 control channels (softpatch)
- For 28 devices with 18 control channels each
- USB port for saving programming data
- Quick programming thanks to 9 movement sequences and 7 integrated color effects (adjustable PAN/TILT position, fade duration, and execution duration)
- Memorization of 32 programmable chases with 100 scenes each
- Manual Chase mode, time-controlled, or music-controlled
- 32 programmable scenes
- Control of 2 levels of DMX devices, each with 18 channels
- 16 DMX channel sliders
- 2 wheels for pan & tilt
- Blackout function

Technical Datasheet

- Sound-controlled via the built-in microphone
- Backlit LCD (2 x 16 characters)
- RDM-compatible (DMX address configuration and identification)
- 3-pin XLR connectors
- Firmware update via USB
- Possible installation in a 3U rack
- Power supply 110-240 V AC, 50/60 Hz ~ via included power adapter
- Consumption 2.7 W
- Number of control channels 512
- Number of memorizable scenes 32
- Number of memorizable chases 32 with 100 steps each
- Audio control via the internal microphone
- DMSS12/RDM output 3-pin XLR connector
- Compatible data storage support USB sticks (FAT32)
- Dimensions 483 x 130 x 82 mm
- Weight 2.2 kg

At FactorLED we ensure that our products have a QUALITY guarantee and offer all the necessary elements for DISTRIBUTION, IMPORT or WHOLESALE, including the technical data sheet of each LED product.

Additional images:

